

LIGHTING PRODUCTS: CONSOLES



Hog 1000

Moving Light Console

The Hog 1000 is designed to control any combination of automated or static lighting fixtures, with moving lights as simple to control as conventional luminaires. This console is the ideal choice to control both simple and complex lighting systems.

Feature List

- WholeHog II Operating System
- Cues, Cue lists, effects and presets can be merged from one show to another
- Split Fade Times on any parameter
- Cue Lists, cue contents, programmer, patch and actual stage output can be displayed on a VDU
- Any fixture can be patched anywhere on the DMX outputs
- User -Definable system defaults
- Multiple fixture types simultaneously supported
- Console self test and diagnostic routines
- Access protection PIN
- Easy to understand command line syntax
- Menu banks of palette buttons give instant access to Beam, Colour, Position and Groups of fixtures LCD's provide continuous feedback on programming and playback status together with cue or palette lists
- All shows can be stored on floppy disk
- Universal power supply 100-240 VAC 47-63 hz
- CE and C tick approved

Specifications

Control Channels	1024
Menu Banks	4
Playback Faders	16
Displays	7
Midi In	1
Midi Through	1
Midi Out	1
DMX Outputs	2
Desk lamp outputs	2
Option Port	1
VDU Output	1
Keyboard Input	1
Trackball/Mouse Input	1
Floppy Disk Drive	1
Dimensions (mm)	908(W) 530(D) 150(H)
Net/shipping weight	18/25kg